

DATA SHEET

impulse switch (remote switches) RS 012-001

to remotely switch consumers up to 16 A Article number 09981042



Function

Latching relays, also called remote switches, are switching relays that switch on due to an electrical pulse at the controller inputs and switch off due to another pulse. The impulse relays (remote switches) in series RS are suitable for switching electrical consumers up to 16 A in intermittent operation. This design of impulse relays is suitable for mounting in in-wall sockets/boxes but also in cable ducts or recessed spaces. This design of impulse relay has local command inputs for switching consumers on and off.

Features

high flexibility thanks to different contact configurations, contour and terminal-compatibility with installation relay program, Option of visual display of operating status via LED, low switching noise and no humming or buzzing, Duty cycle: 100 % with spacer 0,5 mod. widths, switch position indicator on the front, Glow lamps parallel to control keys possible, easy connection thanks to generously dimensioned, captive terminals, connection wires cannot become lodged behind the terminals, easy accessibility for connecting coil supply, protected against direct contact under BGV A3, Quick-snap fastening for the 35 mm mounting rail, Local and central control, two-level groups can be switched (RSZ only)

Mounting

quick fastening to mounting rail, any installation position

Applications

The components offer universal use for control tasks in industrial and building systems as well as in domestic installations. They are especially suitable for switching lighting systems, electric heaters, fans, air conditioning systems, ventilators, heat pumps and glow and gas-discharge lamps.

Notes

The designation for the devices in the RS series includes the rated voltage (first group of digits) and the contact design (final group of digits), which is listed in the following order: normally opened contact, normally closed contact and changeover contact. A "RSo24-110" therefore has a rated voltage of 24 V, one normally opened contact and one normally closed contact, but no changeover contact, The duty cycle is limited to max. 1 h. To reach 100 % duty cycle, the DHDS spacer must be used on both sides, Glow lamps switched in parallel from luminaire switches generate reactive currents that, if excessive, can be offset by a capacitor block to prevent coil overheating.

Accessories


spacers DHDS, capacitor blocks RS

Technical Data

Technical Data	RS 012-001
Series	RS 012
Number of (n.o, n.c.,change- over)	0 0 1
Operating voltage (AC)	12 V
Operating frequency	50 Hz
	control input
Rated voltage (AC)	12 V
Rated impulse withstand voltage	2 kV
Rated power	7 VA (max. 12 VA)
Rated frequency	50 Hz
min. Pulse duration control input	200 ms

RS 012-001
22
8
load circuit
relays
5 mm
typ. < 5 ms (max. 10 ms)
100
250 V (min. 24 V)
min. 24 V
16 A
500 V
4 kV
50 Hz
1.5 W
16 A
1980 VA
900 VA
1105 VA
1020 VA
1700 VA
lift terminal, captive top and bottom (control input, load circuit)
1-wire: 0.5 mm ² 10 mm ²
o.5 mm² 6 mm²
1-wire: 0.5 mm ² 10 mm ²
General data
short-time operation (Duty cycle ≤ 1 h, 100 % with spacer 0,5 mod. widths)
optional
min. 1 · 10 ⁶ switching cycles
min. 40000 switching cycles
-20 °C 45 °C
distribution board housing
Mounting rail (35 mm)
thermoplastic
IP20 (installed: IP40)
18 mm
90 mm
65 mm
60 mm
1
0.132 kg
EN 60715, EN 60669-1

Dimensions



Wiring example



Wiring diagram

Dimensional drawing Group view